

# PRIVACACY & OCCUPANCY SENSOR

**LED**  
TECHNOLOGY

**PIR SENSOR**

180° Field of View  
12 Ft Wide



30 Ft Out

**VACANCY MODE:**  
MANUAL ON  
AUTO OFF  
  
OR  
**OCCUPANCY MODE:**  
AUTO ON  
AUTO OFF



Compatible with:  
LED, Fluorescent  
and Incandescent

**MANUAL SWITCH**

**Features:**

- 2 In 1 Setting Modes: Occupancy or Vacancy
- Built-in OCC/VAC Push-In Button Offers Manual ON or Auto ON and Auto OFF
- Screwless Wall Plate
- Vacancy Mode Complies with CA Title 24 Requirements

**Specifications:**

- 120V/227V AC, 60HZ
- 800W/VA@120V, 1200W/VA@277V, No Min
- LED 400W/VA MAX
- Adjustable time delay Dial
- Adjustable sensitivity Dial
- Light sensing level Dial
- Single Pole or 3 Way Wiring

**Specifications:**

Model#	Description	Case Pack	Color	Size	UPC
SWMS-OCV3W-WH	Motion Sensing Vacancy or Occupancy Sensor, Dual Mode Switch	6 pcs	White	H 4.5" W 2.75" D 1.73	74616080132-2

